

1111



# Disinfect large areas quickly and safely

Mobile disinfection sprayers Made in Germany

www.cmc.pt



available from 1 May 2020



## Mobile Disinfection Sprayers

Suitable for commercial disinfection solutions with a flashpoint higher than 55° C

### constant spray pressure for even, low-mist spray results

- adjustable flow volume
- saves time and money
- protects the environment and health



- spray lance with flat fan nozzle
- 5 m reinforced hose
- PE canister 20 L

**Dimensions:** LxWxH 29 x 25 x 57 cm

### 0 ⊘ 🌑

Accessories: Adaptor set for canister pump ref. 11362 Adapters to 2 inch thread, DIN 51 and DIN 71 threads, with longer suction hose and foot filter

- for large areas in public facilities, schools and buildings
- for machinery and work surfaces in industrial areas between shift changes
- for safety-sensitive areas in health services such as medical practices, hospitals etc.

For more information: cmc@cmc.pt

Additions to our range of disinfection products are being developed! Subject to technical changes. © CEMO 04.20





### Container sprayer 230 V ref. 11356

Spray lance with flat fan nozzle no. 4, spraying angle 110°, approx. 1040 -1370 ml per minute flow rate, and flat fan nozzle no. 2, spraying angle 110° approx. 800 – 1000 ml per minute flow rate

- container volume 20 L
- 230 V power
- 5 m cable length
- pressure control valve 0.3 5 bar
- 5 m reinforced hose
- spray lance with flat fan nozzle
- Dimensions:

LxWxH 56 x 21 x 38 cm

#### Spray Caddy 60 L, 12 V ref. 11359

Battery-operated

Battery capacity 3.3 Ah, sufficient for approximately 60 L ( with nozzle 03) Spray lance with flat fan nozzle no. 3, spraying angle 110°, approx. 1150 ml per minute flow rate, and flat fan nozzle no. 2, spraying angle 110° approx. 800 ml per minute flow rate

- 12 V pump with 100% duty cycle
- LiFePO4 battery with charger
- 8 m reinforced hose

• spray lance with flat fan nozzle **Dimensions:** 

LxWxH 90 x 52 x 37 cm

#### Accessories:

Spare battery ref. 10602 12, 8 V 3.3 Ah Lithium Iron Phosphate battery